

## ST-7000 2-8 Loop Fire Alarm Control Panel

The ST-7000 series is fully expandable from 2 to 8 loops and supplied with 8 on-board sounder circuits, 20 programmable Zonal LEDs with slide-in labels, and 25 System LEDs for information purposes. There are also 8 programmable function buttons with LED indication for confirmation of operation.

The control panel consists of the latest dual flash-based microprocessor technology combined with a high resolution, high contrast, graphical LCD display and tactile keypad providing a simple select & click programming aid for engineer configuration and end-user operation.

Powerful cause-and-effect programming coupled with dynamic zoning, and enhanced Trace Diagnostics makes the panel suitable for a wide range of site applications from small to large complex multi-area systems. Fully programmable onsite via the on-board alphanumeric keypad, or PC-NeT configuration software. An extensive suite of user-friendly Windows based PC software programs has been developed to enhance your experience when using ST-7000 series fire panels. The suite incorporates a number of different programmes to include a configuration, service, logo and virtual panel tool to allow the flexibility of the equipment to be fully explored.

Simply adding a network card allows the panel to communicate with any other ST-7000 fire panel, remote terminal, or network peripheral, such as, ipGateway™ or BMS/graphical interface. The network operates as a true peer-to-peer system and can be configured in a fault tolerant loop or radial format.



### Features

- Fully expandable from 2 - 8 loops via plug-in loop driver boards.
- 20 programmable Zonal / 25 System LEDs with slide-in labels.
- Dedicated loop driver for Apollo or Hochiki protocol support.
- Graphical LCD user interface and support for up to 200 fire zones by default allowing full EN54 compliance without additional hardware.
- Dual flash-based microprocessor technology with real-time clock on-board.
- Dedicated USB & RS232 serial port for direct PC or modem connection.
- Installer friendly Auto-learn, Loop Detection and On-board Scope facility for ease of commissioning and fault finding.
- Fully programmable via the on-board alphanumeric keypad, or PC configuration tools.
- The graphical display can be configured to operate with virtually any language or character set, and allow the installer's logo to be applied using the Logo application software.
- Robust removable equipment chassis with plug-in connectors for simple fixing and cable termination.
- 2 x 5 Amp power supply and charger to EN54 part 4.
- Integral P-Bus for system expansion via available option cards.
- Ad-NeT peer-to-peer network with up to 2000 zones.

## Key Features

Dedicated 2 - 8 Loop	Global Compliance	3 Year Warranty	Programmable Push Buttons
Multiple Languages	Fully Networkable	20 Zonal / 25 System LEDs	Slide-in Labels

## Specification

Base Technology	Dual flash-based processors with real-time clock, trace diagnostics, programmable languages and character sets
Display	White backlit 240 x 64 graphical LCD
LED Indicators	22 red (1 x Fire, 1 x More Alarms, 20 x Zonal Programmable), 1 green (Power), 13 amber and 7 bi-colour (Fault & System)
Controls	Alpha numeric keypad permitting Navigation, Reset, Mute, Silence, Resound, Evacuate, and 4 x Programmable Push ButtonsActual 2
Protocols	Apollo (Xp95 / Discovery), Hochiki ESP, Argus Vega and Nittan Evolution
Number of Fire Zones	2000 when networked (400 max across 8 loops)
Number of loops	Dedicated 2-8 loop control panel
Devices per loop	Protocol dependent
Loop Current	500mA max per loop
On-Board Sounder Circuits	8 x 1 Amp programmable
On-Board Relays	4 x 1 Amp 30v AC/DC programmable (10mA, 5v min) - expandable to 8 using 2 x STP-707
Auxiliary Supply	2 x 24v 500mA 2
Programmable Input	2 x On-board Programmable Input
Programmable Key Switch Inputs	16 volt free digital inputs
Total Available Output Current	2 x 5A maximum available for loop current + sounder outputs + auxiliary supply
Mains Supply	200 - 240v 47-63 Hz AC (+10%, -15% tolerance) 1.4A max
Battery Capacity	2 x 24V 4Ah internal (min), 2 x 24V, 18Ah internal (max), or 1 x 24V 45Ah internal (max) and 1 x 24V 45Ah external (max) using optional battery enclosure
Charger Current	2 x 2.0A temperature compensated
Serial ports	2 x on-board RS232 connection for PC, modem, IP or portable printer
USB Interface	2 x USB B type connection for PC communication
Programming	On-board keypad or PC running Windows tools
Event Log	2 x 5000 Event & Diagnostic + 500 Fire
Printer (Optional)	On-board
Enclosure / Colour	Steel IP30 / RAL7035
Cable Entry (20mm knockouts)	30 x top, 6 x rear, 3 x bottom plus 2 x double knockout rear
Size H x W x D mm	750 x 450 x 190
Metalwork Options	Flushing bezel, battery box, utility enclosure, termination enclosure and rack mount

## Order Codes and Options

ST-780x*:	Multi Loop Panel in Standard Enclosure with standard network cards fitted	x:	Add loop driver quantity 2 - 8
		/FT:	Add Fault-tolerant network cards
		*:	Add V for Vega, and add N for Nittan Evolution protocol